



Delivered without miniature WSB markers

The 750-495 3-Phase Power Measurement Module measures electrical data in a three-phase supply network. The voltage is measured via network connection to L1, L2, L3 and N. The current of the three phases is fed to IL1, IL2, IL3 and IN (two clamping points each +,-) via current transformers or via Rogowski coils for the 750-495/000-002 module. The 750-495 Module transmits metrics (e.g., reactive/apparent/effective power, energy consumption, power factor, phase angle, frequency, over-/undervoltage) directly into the process image, without requiring high computing power from the controller. Both comprehensive metrics and harmonic analysis up to the 41st harmonic permit extensive network analysis via the fieldbus.

Metrics allow the operator to optimize the supply to a drive or machine, protecting the system from damage and failure. Insulation failures can be detected and prevented via current measurement performed in the neutral conductor. The 4-quadrant display indicates the type of load (inductive, capacitive) and whether it is an energy consumer or producer.

Description	Item No.	Pack. Unit	
3-Phase Power Measurement Module (690V/1A)	750-495	1	
3-Phase Power Measurement Module (690V/5A)	750-495/000-001	1	
3-Phase Power Measurement Module (690V/RC) Rogowski Coils	750-495/000-002	1	
Accessories	Item No.	Pack. Unit	
Miniature WSB Quick marking system	plain	248-501	5
	with marking	see Full Line Catalog AUTOMATION 2012/2013	
Approvals			
Conformity marking	CE		
Technical Data			
Wire connection	CAGE CLAMP®		
Cross sections	0.08 mm ² ... 2.5 mm ² / AWG 28 ... 14		
Strip lengths	8 ... 9 mm / 0.33 in		
Width	24mm		
Weight	48.5 g		
EMC: CE - immunity to interference	acc. to EN 61000-6-2 (2005)		
EMC: CE - emission of interference	acc. to EN 61000-6-3 (2007)		

Technical Data	
Number of measurement inputs	7 (3 voltage measurement inputs, 4 differential current measurement inputs)
Rated voltage	$V_{LN} = 400 \text{ V AC}$; $V_{UL} = 690 \text{ V AC}$
Input resistance voltage path (typ.)	1428 k Ω
Measuring current (max.)	1 A (750-495) 5 A (750-495/000-001) Rogowski Coils RT500/RT2000 (750-495/000-002)
Input resistance current path (typ.)	22 m Ω (750-495) 5 m Ω (750-495/000-001) 44 k Ω (750-495/000-002)
Resolution	24 bits
Frequency range - frequency of supply network	45 Hz ... 65 Hz
Frequency range - analysis of harmonics	0 Hz ... 3300 Hz
Max. operating frequency	15.9 kHz
Signal form	any periodic signals (taking the maximum frequency into account)
Measuring error for current and voltage	Max. 0.5 % (of the upper range value)
Measuring procedure	True RMS measurement
Measuring cycle time	Adjustable for arithmetic mean value, Min_Max_Values
Measured values	Line-to-line voltage, power output, energy, power factors, mains frequency, harmonic analysis (up to the 41st harmonic), THD
Power supply	via system voltage internal bus (5 V)
Current consumption (internal)	100 mA
Rated surge voltage	6 kV
Overvoltage category	III
Degree of pollution	2
Bit width	2 x 128 bits data 2 x 64 bits control/status